

GTW - INSTALLATION INSTRUCTIONS

IMPORTANT SAFEGUARDS

- THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.
- DISCONNECT POWER BEFORE BEGINNING INSTALLATION.
- FIXTURE MUST BE INSTALLED IN COMPLIANCE WITH THE NATIONAL ELECTRIC CODE AND ANY LOCAL CODES.
- TO BE INSTALLED ONLY BY A QUALIFIED ELECTRICIAN.
- PROPER GROUNDING IS REQUIRED TO INSURE PERSONAL SAFETY.
- READ ALL FIXTURE MARKINGS AND LABELS TO ENSURE CORRECT INSTALLATION OF FIXTURE.
- RISK OF FIRE, USE A MINIMUM OF 90C SUPPLY CONNECTORS.
- MAXIMUM MOUNTING HEIGHT OF 8 FT. WHEN AN EMERGENCY PACK IS PROVIDED

SAVE THESE INSTRUCTIONS

SURFACE MOUNT INSTALLATION

- REMOVE SCREWS SECURING MOUNTING PLATE ASSEMBLY TO HOUSING.
- DISCONNECT PUSHWIRE CONNECTOR AND REMOVE MOUNTING PLATE ASSEMBLY FROM HOUSING.
- REMOVE WIREWAY COVER FROM MOUNTING PLATE ASSEMBLY AND SET ASIDE.
- LOCATE MOUNTING HOLES IN MOUNTING PLATE AND POSITION OVER J-BOX (IF APPLICABLE). MARK HOLE LOCATIONS AND DRILL HOLES IN MOUNTING SURFACE.
- REMOVE K.O. FROM MOUNTING PLATE.
- FASTEN MOUNTING PLATE TO MOUNTING SURFACE WITH APPROPRIATE HARDWARE (BY OTHERS).
- POSITION WIREWAY COVER OVER MOUNTING PLATE.
- CONNECT HOT, NEUTRAL AND GROUND WIRES TO BUILDING CONDUCTORS.
- REINSTALL WIREWAY COVER TO MOUNTING PLATE.



- CONNECT PUSHWIRE CONNECTOR AND REINSTALL HOUSING TO MOUNTING PLATE ASSEMBLY.
- CAULK BETWEEN MOUNTING SURFACE AND FIXTURE (IF NECESSARY) TO SEAL THE UNIT IN UNIQUE SURFACE CONDITIONS.

