## 1 חוו2**-**R


**CONFINEMENT SERIES** 


WALL LUMINAIRE CLAMSHELL DESIGN FOR MIN. TO SUPERMAX SECURITY FLUORESCENT/LED





### **DIMENSIONAL DATA**





## **ORDERING INFORMATION**

Project:	
Түре:	
Product:	
Approved:	
Date:	

## **FEATURES**

The New Star " RUD2-RUD4" Confinement clamshell fixture is designed for security application requiring up and down light distributions

- 18-12 gauge die formed steel or stainless steel nonclam shell housing with full length continuous staked piano hinge with welded end
- · Rounded housing shape designed to withstand physical abuse
- 16 gauge full length continuous staked piano hinge with welded ends

## APPLICATION

- Detention Centers Confinement
- Psychiatric Wards Public Housing Complexes Athletic Facilities

SPECIFICATION FEATURES

#### HOUSING:

Die formed, seam welded, and ground smooth (specify material and gauge). Incorporates a removable reflector unitized with all electrical components for easy installation and maintenance.

BACKPLATE: Die formed with contraband drop slot and embossed mounting holes(materials and gauge to match housing). Security caulking between ceiling and fixture is not required with this back plate design.

#### HINGE:

16 gauge full length continuous, staked piano hinge, with welded ends. to prevent removal (material to match housing).

### LENS / LENS RETENTION:

Lens per specification (see options) and secured by "Z" retainers with weld studs spaced six inches apart for maximum strength.

#### ELECTRONICS: Fluorescent: Electronic Ballast <10% THD standard. RIF

available. Lamps by others.

• Lens held in place with Z-Channel and weld studs

- Torx head center pin screws standard
- Black Neoprene gasket around door frame to prevent light leaks
- Wet location optional
- Transportation Applications 
  Locker Rooms

## LED:

Available in three standard color temperatures 3500°K,4000°K & 5000°K. Other color temperatures available, consult factory.

#### LED NIGHT LIGHT:

Integrated switch allows light selection at 100%,70%,40% and 10% levels

## GASKET:

Black Neoprene gasket around door frame to prevent light leaks

## FASTENERS:

Tamper resistant countersunk, flat head Torx screws, with center pin reject

## FINISH:

White powercoat finish following an iron phosphate pre-treatment.



Product Family	Gauge	# of	Lamps	Lamp Type	# Ballasts	s/Drivers
RUD_	-					
RUD2 9-7/8" x 25-3/16" x 8-11/16" RUD4 9-7/8" x 49-3/6" x 8-11/16"	B = 14 Ga.CRS G = 18 Ga.SS C = 16 Ga.CRS (Brushed) D = 18 Ga.CRS H = 14 Ga.SS E = 14 Ga.SS (Painted) (Brushed) J = 16 Ga.SS F = 16 Ga.SS (Painted) (Brushed) K = 18 Ga.SS (Painted)	$ \begin{array}{l} \textbf{RUD2-RUD4} \\ \textbf{A} = 1 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Down} \\ \textbf{B} = 1 \ \textbf{Up} \ / \ \textbf{2} \ \textbf{Down} \\ \textbf{C} = 2 \ \textbf{Up} \ / \ \textbf{2} \ \textbf{Down} \\ \textbf{D} = 2 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Down} \\ \textbf{D} = 2 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Down} \\ \textbf{F} = 1 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Down} \\ \textbf{F} = 1 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Down} \\ \textbf{ED RUD2:} \\ \textbf{LA} = 1 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Dn}(25W) \\ \textbf{LB} = 1 \ \textbf{Up} \ / \ \textbf{2} \ \textbf{Dn}(37.5V) \\ \textbf{LC} = 2 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Dn}(37.5V) \\ \textbf{LC} = 0 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Dn}(37.5V) \\ \textbf{LF} = 0 \ \textbf{Up} \ / \ \textbf{1} \ \textbf{Dn}(12.5) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{0} \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \\ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \ \textbf{LF} = 1 \ \textbf{Up} \ / \ \textbf{Dn}(12.5V) \ \textbf{LF} = 1 \ \textbf{Up} \ \textbf{Up} \ \textbf{Up} \ \textbf{LF} = 1 \ \textbf{Up} \ \textbf{Up}$	V)	Fluorescent RUD1:      Fluorescent RUD4:        18 = 18W Triple Gx24q-2      32 = Linear 32W T8        8Q = 18W Quad G24q-2      28 = Linear 32W T5        26 = 26W Triple Gx24q-3      54 = Linear 54W T5 HC        6Q = 26W Quad G24q-3      LED:        32 = 32W Triple Gx24q-4      40 = White 3500° K        42 = 42W Triple Gx24q-4      40 = White 4000° K        Fluorescent RUD2:      50 = White 5000° K        17 = Linear 17W T8      14 = Linear 14W T5        24 = Linear 24W T5 HO      40 = 40 Twin 2Gx11	Fluorescent: 1 = Ballast 2 = Ballast	LED: 1 = Driver 2 = Driver

K.O.

	Outer Lens	Inner Lens	Voltage	Options	
-	/	-	-		
	Ø = No Lens      4 = .500 Clear Poly.        A = .125 Clear Poly.      5 = .187 Clear Temp.Glass        B = .156 Clear Poly.      6 = .250 Clear Temp.Glass        1 = .187 Clear Poly.      7 = .375 Clear Temp.Glass ^        2 = .250 Clear Poly.      8 = .500 Clear Temp.Glass ^        3 = .375 Clear Poly.      9 = .750 Clear Temp.Glass ^		12 = 120V 27 = 277V 34 = 347V ■ UN = Universal (120V-277V	DB = Ballast: Dimming (0-10V) * E1 = Emergency Ballast (450 Lumens) * ◀ E2 = Emergency Ballast (1350 Lumens) * ◀ EL1 = Emerg. Bat. LED Low EL2 = Emerg. Bat. LED High PR = Programmable Ballast - Rapid Start AH = Allenhead Screws	FZ = Fuse Holder * WL = Wet Location UV = .005 UV Absorbing Overlay SL = Flush Button Switch (Left) SR = Flush Button
*	O	Consult factory for T5 availability Cannot use with option E or F # of lamps configuration Not available in LED	1	NL = Fluorescent Night Light * LN = LED Night Light. Consult factory for available color / temperatures.	Switch ( Right)



Specifications and Dimensions are subject to change without notice. For additional options and dimensional details please consult your New Star Lighting Representative. For specific electronic ballast, specify brand and catalog number.

# Rud2-Rud4



Based on a .125 Clea	Based on a .125 Clear Polycarbonate Outer lens / .125 Prismatic Acrylic Inner lens				
# LED BOARDS	# ROWS UP	# ROWS DOWN	TOTAL WATTAGE	EFFICACY	DELIVERED LUMENS
RUD2:					
LA	1 RW	1 RW	25.0W	110	2,750 LMS
LB	1 RW	2 RW	37.5W	110	4,125 LMS
LC	2 RW	2 RW	50.0W	110	5,500 LMS
LD	2 RW	1 RW	37.5W	110	4,125 LMS
LE	0 RW	1 RW	12.5W	110	1,375 LMS
LF	1 RW	0 RW	12.5W	110	1,375 LMS
RUD4:					
LA	1 RW	1 RW	50.0W	110	5,550 LMS
LB	1 RW	2 RW	75.0W	110	8,250 LMS
LC	2 RW	2 RW	100.0W	110	11,000 LMS
LD	2 RW	1 RW	75.0W	110	8,250 LMS
LE	0 RW	1 RW	25.0W	110	2,750 LMS
LF	1 RW	0 RW	25.0W	110	2,750 LMS

TAKE AN ADDITIONAL 20% OFF DELEIVERED LUMENS WHEN SPECIFYING THE LC3 LENS